

Field Mounting Rate Totalizer

Model 202Di

Features

- CENELEC, CSA US/C, approved
- Displays Rate, Total and Accumulated Total
- Battery, Loop or DC powered
- Intrinsically safe version - 202Di
- Watertight to IP67 (Nema 4X)
- Wall, pipe or flowmeter mounting
- Fully programmable
- 4-20mA output
- High & low alarms
-  Compliant



Overview

The 202Di Field Mounting Rate Totalizer requires no external power and is designed to operate with turbine, positive displacement and paddle-wheel flowmeters in applications such as irrigation systems and pipelines, and as a replacement for mechanical registers.

Battery, Loop or DC powered

The standard 202Di is powered by long-life lithium batteries. Alternatively, the 202Di can be loop powered via an optional 4-20mA output, or powered from a 9-28 Volts DC supply.

For installation in hazardous areas a certified intrinsically safe version is available. The intrinsic safety approvals cover a wide range of inputs and both the 4-20mA output and relay outputs.

Watertight field mounting enclosure

The 202Di Rate Totalizer is housed in a rugged yet attractive IP67 (Nema 4X) rated polycarbonate enclosure which is completely watertight.

This enables the instrument to be mounted directly on the flowmeter, panel mounted or wall mounted using a special universal bracket. A 2" pipe mounting bracket is also available.

Fully user programmable

K-factor, decimal point positions, filter constants and time base are fully user programmable.

Rate and **Totals** can also be displayed in different engineering units such as gallons per minute and barrels.

Field Mounting Rate Totalizer

Model 202Di

Frequency to current conversion

The 202Di loop powered Rate Totalizer makes an excellent **Frequency to Current** Converter particularly for low frequency inputs from positive displacement or turbine flowmeters.

Because the 202Di calculates the flow rate by measuring the time interval between input pulses, it is able to provide a very stable and accurate 4-20mA output for low frequency inputs.

Time interval measurement also means that the 202Di will have a fast response to changes in flow rate, although the response can also be limited, where necessary, via the digital filtering.

Digital filtering enhances rate accuracy

Frequency fluctuations caused by pulsating flow through a flowmeter, often makes the Rate impossible to read with any precision.

The 202Di has a digital filter which averages out these fluctuations and enables the rate to be read to a four digit accuracy.

The degree of filtering is fully programmable and therefore, highly accurate and stable readings can be obtained without excessive lag. For versions with a 4-20mA output, the current output is also filtered.

Versions Available

Battery Powered

The battery version of the 202Di is designed for operation where external power sources are not available. It derives its power from two lithium battery packs which provide sufficient power for up to 5 years.

Low battery power condition is signalled to the operator by a message on the LCD and battery replacement is easily carried out in the field even in hazardous areas.

4-20mA Output Loop Powered

The 4-20mA output version draws its operating power from the 4-20mA loop and uses lithium batteries for back-up if the 4-20mA loop is interrupted.

The instrument provides a 2-wire re-transmission of the flow rate. Both the 4mA and 20mA points are fully programmable so that the output can span across the entire range, or alternatively, across a small section of the operating range.

DC Powered

The DC powered version will operate from an external power source between 9 and 28 Volts and draws no more than 4mA. This enables the 202Di to be powered from AC mains adapters and eliminates the need to run mains voltages in the field.

Lithium batteries provide back-up if the DC power is interrupted.

Solid State Relay Outputs

Both the 4-20mA output version and the Dc powered version are provided with two solid state relay outputs. The solid state relays provide high and low flow rate alarms or, alternatively, a pulse output and a low flow rate alarm. The outputs can sink up to 200mA and can be used to power external relays, audible alarms or counters. The outputs are internally protected against voltage spikes caused by relays and coils.

Both outputs are separately isolated via opto isolators.

The switching points can be programmed during the set-up mode. If programmed for a pulse output, the pulse can be selected as either unscaled (raw pulse input) or scaled. The maximum pulse width which is automatically set as:

1mSec if output > 50Hz

10mSec if output = 5-50Hz

100mSec if output < 5Hz

General

Display - Total	7 digit 10mm (0.4") high LCD (continuously powered). Note: The Resettable Total is resettable from the front panel and the Accumulated Total is displayed when the ACCUM TOT key is pressed.
Display - Rate	4 digit 8.5mm (0.33") high LCD (continuously powered).
K-factor Range	The pulses per unit of measure (eg. pulses /gallon) is programmable in the range 0.000001 to 999,999.
Decimal Points	Fully programmable for Rate and Total.
Time Base	Rates can be displayed in units per second, minute, hour or day.
Frequency Range	0.01Hz to 10kHz.
Signal Type	Switch settable for sine wave (15mV P-P minimum), open collector, reed switch or pulse.
Interference	CE Compliance.

Physical

Operating Temperature	-20 to 60°C.
Enclosure	
Dimensions:	98mm (3.9") high x 152mm (6.0") wide x 43mm (1.7") deep.
Protection:	IP67 (Nema 4X) watertight.
Cable Entry:	By cable glands.
Materials:	Polycarbonate and ABS.
Mounting Options	
Wall:	Wall mount bracket with cable glands.
Pipe:	A galvanized metal bracket enables the 202Di to be attached to a 2" vertical or horizontal pipe.
Panel:	Two mounting brackets are provided and terminals are accessible on the rear of the enclosure. Note that the panel mount version is not watertight.

Battery Powered Version

Battery Type	2 x Lithium battery packs
Battery Life	5 years

Loop Powered 4-20mA Output Version

Scale	The 4mA and 20mA points are programmable.
Resolution & Linearity	0.05% of span
Accuracy	0.05% of span at 25°C
Update Time	0.5s
Connection	2-wire
Voltage Across Output	28V DC maximum
Voltage Drop	9V maximum
Memory Backup	Lithium battery

DC Powered / Alarm or Pulse Output Version

Outputs	2 x solid state relay outputs suitable for driving DC solenoids or external relays. The outputs provide fully programmable high and low flow alarms or a pulse output and low alarm.
Pulse Output	Scaled or unscaled pulse output, 500Hz maximum. Pulse width depends on output frequency and varies from 100mSec to 1mSec.
Switching Power	200mA, 30V DC maximum.
Saturation Voltage	0.8V DC across outputs when in the "on" state.
Isolation	Both outputs are separately isolated.
DC Power Input	9-28V @ 4mA maximum.
Memory Backup	Lithium battery.

Hazardous Area Approval (Model 202Di)

Type of Approval	
CENELEC	EEx ia IIB T4.
CSA _{US/C}	Class 1, Groups C and D.
SAA	Ex ia IIB T6.
Maximum Ambient	60°C

Maximum Input Parameters

(For Certified IS coil or other Certified IS sensors which produce a pulse output)

U _o = 10.0V	Li = 0mH
I _o = 9.0mA	Ui = 24V
C(ext) = 60µF	Ii = 20mA
L(ext) = 1.5H	Pi = 320mW
	Ci = 0.002µF

Note: Devices such as reed switches, which can be classed as "Simple Apparatus" as defined in the CENELEC standard EN50020, can be connected to the Model 202 without additional certification.

The Model 202 has two pulse inputs, a high impedance balanced input for coils and pulse input for other devices. It is not permissible to connect to both inputs at the same time.

Maximum Input Parameters

(For Certified Namur proximity sensors)

Ui = 28V
Ii = 93mA
Pi = 653mW

Important: Specifications are subject to change without notice.

